

TAIE

www.fa-taie.com
www.fa-taie.com.tw

High New Feeling!

First White LED Module in the world

**Outstanding Excellent
Top Elegance**

FY

**Digital PID Temperature Controllers
/ Process Controllers**

High Quality High Reliability



FY401



TAIE

FY900



FY801



FY701



FY400



FY700



FY800



FY900



FY600



BEST CHOICE FOR PROCESS AND TEMPERATURE CONTROL

Application:Control temperature , humidity , pressure , flow and PH.

FY series controllers are microprocessor based controllers. Which have been designed with high accuracy input , various output selection , useful options and good reliability at a competitive price.

FY series use "PID+FUZZY" algorithm to implement excellent control. The output status is displayed on the built in "Bar-Graph" display.

FY series not only provide the basic control output selections but also plus advanced options such as "Motor Valve Control" , "SCR/TRIAC Trigger" , and "Programmable RAMP/SOAK".

FY series support MODBUS protocol. Communication with HMI is more convenient. New additional HBA function with competitive price, user can upgrade system safety easy.

Add functional Module stand & jumper, supply customer easy to change Relay SSR.4~20mA/TC.DPT100. Add new white LED module break the traditional vision, opening the new LED century.

Available in 4 sizes , the models and sizes are as below:

FY401 : 48X48mm (DIN 1/16)

FY801 : 48X96mm (DIN 1/8)

FY701 : 72X72mm (DIN 3/16)

FY901 : 96X96mm (DIN 1/4)

Available in 7 sizes , the models and sizes are as below:

FY400 : 48X48mm (DIN 1/16)

FY600/800 : 48X96mm (DIN 1/8)

FY700 : 72X72mm (DIN 3/16)

FY900 : 96X96mm (DIN 1/4)

FY100 : 175X110mm

FY101 : 90X90mm



FY401

FY701

FY801

FY901

FY600

FY400

FY700

FY800

FY900

CE UL Approval & free power

All models get CE approval.

Operate on any voltage from AC 85~265V at 50/60Hz. DC 24V is also available(optional function).

IP65 Proof




IP65 dust & water proof is available for all models(optional function).

Heater Break Alarm (HBA)




Heater current flowing through CT can be displayed on controller. If heater current is less than HBA set value, AL1 will be activated (optional function).

MODBUS Communication



FY series support both MODBUS RTU and MODBUS ASCII protocol. Communication between controller and HMI or other equipment is more convenient(optional function).

Autotuning (AT)



AT Function can calculate the optimize PID value for your control system, without trying

Auto/Manual mode



Click!

Conveniently switched between auto/manual output mode by clicking "A/M" key(except "FY400/FY401").

Various Indication Lamps



Real time monitor the status of output(OUT1/OUT2),AT,alarm (AL1/AL2/AL3),manual output (MAN) and program(PRO).

Bar-Graph



Output percent displayed on the bar-graph in 10 LEDs resolution(except "FY400/FY401").

High Accuracy

Input with 14bit A/D resolution,0.2% accuracy of FS. Built in "AutoZero-AutoSpan" function keep good accuracy.

Data Lock Function

All parameters are separated in 3 operation levels. Each parameter can be hidden or locked to prevent unauthorized changes.

Features

FY / FY1 Series


Digital PID Controller

Various I/O Types



Peripheral Options

Remote SV




Transmission




Communication

(RS485 Communication)
MODBUS Protocol




Communication (TTL Communication)

Up to 10 controllers can be connected.
Max length 1M.



Special Application

Ramp/Soak Program




There are 2 patterns by 8 segments can be used in ramp/soak program.




There are 2 patterns can be linked together as 16 segments in ramp/soak program.


Heating and Cooling Control



Motor Valve Control



SCR/TRIAC Trigger



Method 1φ / 3φ Zero Cross Control
Method 1φ / 3φ Phase Angle Control

Features

FY / FY1 Series



Digital PID Controller

Easy to change Relay/SSR/4~20mA 3 types of OUTPUT




EX: Relay → SSR


①




②




③




④




⑤




⑥




⑦



⑧



⑨




1. Pull controller out from the case.

2. Turn controller to see the module stand.
3. Relay Module has a spring clip to lock it.
4. Take the spring clip to left.
5. Open the spring clip to show Relay.

6. Pull the Relay out.
7. Insert SSRdrv Module. (The front of two aperture is parallel)
8. Insert the module gently than push down to the base.
9. Make sure it's bilateral.(Volt & mA Module don't need spring clip)


Input Type Change of TC ↔ RTD

Convenient Installation




New High Light LED Module Display

Provide Red & white light to choose




To mount panel easily



1. Take out the main body from outer case: adjust the jumper to the correct place
2. Start power after setting jumper to the correct place
3. Amend the input type from the front membrane to enter in Level 3 to set.
4. Please be sure to cut off power and start again after amending input type so that the new parameters could be effective.
5. To change input type of TC or RTD is available but linear input is unavailable. Please ask our local distributor for help.


Excellent Control

Fuzzy Logic




Built in fuzzy logic suppress the overshoot due to SV changes or external disturbance.

Autotuning (AT)



When autotuning acts, it will make PV hunting 1~2 cycle to calculate optimize PID value. To protect user's device, FY series controller can perform PV hunting below SV by setting AT bias value(ATL).

Limit Setting



Built in output limit function. Use this function to get different gradient output and set limit for output.


Appearance

FY / FY1 Series


Digital PID Controller

Parts Description

FY400 (Red light)
FY401 (White light)




FY600 (Red light)



FY800 (Red light)
FY801 (White light)



FY700/900 (Red light)
FY701/901 (White light)





SYMBOL	NAME	FUNCTION
PV	① Measured value (PV)display	Displays PV or various parameter symbols(Red)
SV	② Setting value (SV)display	Displays SV or various parameter values(Green)
SET	③ Set Key	Used for parameter calling up and set value registration
A/M	④ Auto/Manual key	Switches between Auto(PID) output mode and Manual output
<	⑤ Shift Key	Shift digits when settings are changed
V	⑥ Down Key	Decrease numbers (*Only for programmable controller)
A	⑦ Up Key (*Program Run)	Increase numbers (*Only for programmable controller)

SYMBOL	NAME	FUNCTION
OUT1	⑧ OUT1 lamp	Lights when OUT 1 is on(Green)
OUT2	⑨ OUT2 lamp	Lights when OUT 2 is on(Green)
AT	⑩ Autotuning lamp	Lights when Autotuning is activated(Orange)
AL1	⑪ Alarm 1 lamp	Lights when Alarm 1 is activated(Red)
AL2	⑫ Alarm 2 lamp	Lights when Alarm 2 is activated(Red)
AL3	⑬ Alarm 3 lamp	Lights when Alarm 3 is activated(Red)
MAN	⑭ Manual output lamp	Lights when manual output is activated (Orange)
PRO	⑮ *Program Running lamp	*Flashes when program running (Only for programmable controller)
OUT1%	⑯ Output 1% Bar-Graph display	Output 1% is displayed on 10-dot LEDs



External Dimension

Unit : mm



FY400 (Red light)
FY401 (White light)






FY600 (Red light)






FY700 (Red light)
FY701 (White light)





FY800(Red light)
FY801(White light)



FY900(Red light)
FY901(White light)



FY100
FY101
(Require KA601
External Operating Box)







Terminal Arrangement

FY / FY1 Series





Digital PID Controller

FY400 (Red light) / FY401 (White light)


FY700 (Red light) / FY701 (White light)




FY600.800 (Red light) / FY801 (White light)



FY100



FY101



When AL3 Function enable, RS485 Function move to Alarm board.

Specifications

FY / FY1 Series

Digital PID Controller

※ FY400, FY600, FY700, FY800, FY900 Red light Series / FY401, FY701, FY801, FY901 White light Series

Standard Spec.

Model	FY400/401	FY600	FY700/701	FY800/801	FY900/901	FY100	FY101	
Dimension	48X48mm	96X48mm	72X72mm	48X96mm	96X96mm	175X110mm	90X90mm	
LED Display(PAT.)	high light technology, Red/Green/Orange with in one Module					Require KA601 External Operating Box		
Supply voltage	AC 85~265V , DC24V (Optional)					AC 85~265V		
Frequency	50/60 HZ							
Power Consumption	approx 4VA							
Memory	Non-volatile memory E ² PROM							
Input	Accuracy : 0.2%FS, Sample time : 250ms							
TC	K , J , R , S , B , E , N , T , W5Re/W26Re , PL2 , U , L							
RTD	DPT100 , JPT100 , JPT50							
mA dc	4~20mA , 0~20mA							
Voltage dc	0~1V , 0~5V , 0~10V , 1~5V , 2~10V -10~10mV , 0~10mV , 0~20mV , 0~50mV , 10~50mV							
DP Position	0000 , 000.0 , 00.00 , 0.000 (available for mA or Voltage dc input)							
Output 1	Main control output							
Relay	SPST type	SPDT type 3A , 220V , electrical life : 100,000 times or more(under the rated load).						
Voltage Pulse	For SSR drive. ON:24V , OFF:0V , maximum load current:20mA.							
mA dc	4~20mA , 0~20mA .Maximum load resistance:560 Ω							
Voltage dc	0~5V , 0~10V , 1~5V , 2~10V. Maximum load current:20mA.							
Alarm 1	SPST type	SPDT type	SPST type	SPDT type 3A , 220V , electrical life : 100,000 times or more(under the rated load).			SPST type	
Control algorithms	PID , P , PI , PD , ON/OFF(P=0) , FUZZY							
PID range	P:0~200% , I:0~3600 Secs , D:0~900 Secs							
Isolation	Output terminal (control output , alarm ,transmission) and Input terminal are isolated separately.							
Isolated resistance	10M Ω or more between input terminals and case(case) at DC 500V 10M Ω or more between output terminals and case(case) at DC 500V							
Dielectric strength	1000V AC for 1 minute between input terminals and case(case) 1500V AC for 1 minute between output terminals and case(case)							
Operating temperature	0~65°C / 0~50°C							
Humidity range	20~90% RH							
Weight (approx)	approx 150g	approx 225g			approx 300g	approx 130g	approx 80g	

Optional Spec.

Model	FY400/401	FY600	FY700/701	FY800/801	FY900/901	FY100	FY101	
RAMP/SOAK Program	2 Patterns with 8 segments each . The 2 patterns can be linked together as 16 segments use							
Output 2	For heating and cooling control use							
Relay	SPST type							
Voltage Pulse	For SSR drive. ON:24V , OFF:0V , maximum load current:20mA.							
mA dc	4~20mA , 0~20mA .Maximum load resistance:560 Ω							
Voltage dc	0~5V , 0~10V , 1~5V , 2~10V. Maximum load current:20mA.							
Alarm 2	SPST type	SPDT type			SPST type			
Alarm 3	None	SPST type						
Heater Break Alarm (HBA)	Display Range of Heater Current:0.0~99.9A , Accuracy : 1%FS Included CT :SC_80_T (5.8mm dia , 0.0~80.0A) or SC_100_T(12mm dia , 0.0~99.9A) Alarm Relay : AL1							
Transmission	Available for PV or SV transmission							
mA dc	4~20mA , 0~20mA. Maximum load resistance : 560 Ω							
Voltage dc	0~5V,0~10V,1~5V,2~10V. Maximum load current : 20mA.							
Remote SV Input	4~20mA , 0~20mA , 0~5V , 0~10V , 1~5V , 2~10V are available							
Communication	Protocol : MODBUS RTU,MODBUS ASCII, TAIE Interface : RS232 , RS485 , TTL Baudrate : 38400, 19200 , 9600 , 4800 , 2400 bps. 8 bit , Start bit : 1 bit , Parity : Odd or Even , Stop bit : 1 or 2 bit							
WaterProof/DustProof	IP65					None	None	

Order Information

FY / FY1 Series

Digital PID Controller

Model & Suffix codes

* : Block means optional functions with additional charge

* HBA : Heater Break Alarm(HBA must use AL1 as alarm relay)

Combination of options and models

Available — Not available

* Remote SV function is not available if HBA Function has been specified.

Input type table

